

BlackPepper 6 DATASHEET

BKP6-AX2AX2-2450




IEEE 802.11 a/b/g/n/ac/ax

High-Performance, Dual independent Radio operating in ISM 2.4 GHz license-free Band and 4.9/5 GHz Bands, 2x2 MU-MIMO



Optimized SWaP-C

Size, Weight, Power, Cost
Optimized Radio Module



Industrial grade

-40 deg C to +85 deg C
operation temperature

dun & bradstreet



VIZMONET PTE LTD

21 Woodlands Close, #03-01, Primz Biz Hub, Singapore 737 854
+65 6255 0581 | enquiry@vizmonet.com | <https://vizmonet.com>

HW REV# 02.00
Last updated on Apr-19-25

SWaP-C Optimized Design



Industry Standard Connectors for Power, USB and Ethernet Signals



Additional Heatsink Options

TECHNICAL SPECIFICATION

RADIO MODULE – GENERAL INFO	
Radio chipset	Qualcomm IPQ 6028 – Quad Arm Cortex A53 at 1.8 GHz (CPU) QCA 8081 (Ethernet PHY)
NOR Flash	SPI NOR Flash, 32 MB
NAND Flash	NAND Flash, 256 MB
RAM	DDR3L, 1 GB
Operating System	Linux, OPENWRT, supports open source ath11K Linux driver
Security	AES 128, 256, SHA 1-96, 128, 256, 512, CCM and GCM operation FIPS level 2 certification
Operating frequency – 11 b/g/n/ac/ax	2400 MHz to 2483.5 MHz (2S, MU-MIMO)
Operating frequency – 11 a/n/ac/ax	4900 MHz to 5850 MHz (2S, MU-MIMO)
Data rate -11b	1 Mbps, 2 Mbps, 5.5 Mbps, 11 Mbps
Data rate-11g	6Mbps, 9Mbps, 12Mbps, 18 Mbps, 24Mbps, 36Mbps, 48Mbps, 54Mbps
Data rate-11n	MCS0, MCS1, MCS2, MCS3, MCS4, MCS5, MCS6, MCS7
Data rate-11ac	MCS0, MCS1, MCS2, MCS3, MCS4, MCS5, MCS6, MCS7, MCS8, MCS9, MCS10, MCS11
Data rate-11ax	MCS0, MCS1, MCS2, MCS3, MCS4, MCS5, MCS6, MCS7, MCS8, MCS9, MCS10, MCS11,
Channel BW – 2.4 GHz, 4.9 GHz	5 MHz/10 MHz/20 MHz /40 MHz
Channel BW – 5 GHz	5 MHz/10 MHz/20 MHz /40 MHz/80 MHz
Compliance	RoHS, MIL-STD-810H Shock & Vibration
MAC ID	74E277 Series
INTERFACE SPECIFICATIONS	
Power , Operating Voltage	DC in, 9V to 30V
Total DC Power Consumption	21W (Excluding USB Add-on)
RF Antenna connector	x4 SMA Female (Jack) connectors
ENVIRONMENTAL SPECIFICATIONS	
Operating Temperature Range	-40 deg C to +85 deg C
PHYSICAL SPECIFICATIONS	
Mechanical Dimension	(L) 90 mm x (W) 50 mm x (D) 11.4 mm (excluding SMA connectors)
Weight	100g
REGULATORY INFORMATION	
Compliance	In Progress
PACKAGING INFORMATION	
No of units	TBD

ORDERING INFORMATION

BKP6-AX2AX2-2450

BlackPepper 6, Dual Independent, 2x2 MU-MIMO,
IEEE 802.11 a/b/g/n/ac/ax, 2.4 GHz, 5 GHz Bands, 30 dBm

RADIO SPECIFICATION

TX/RX Specification (11b/g) – 2412 MHz to 2462 MHz

TX Power per chain (SISO mode), ± 2 dBm.

DC power consumption refers to the total DC power drawn by the module when operating in 2x2 MU-MIMO mode at 2.4 GHz and it includes the ideal mode power consumption.

RX Sensitivity per chain (SISO mode), ± 2 dBm.

Data Rate	Modulation	TX Power (dBm)	DC Power Consumption (Watts)	RX Sensitivity (dBm)
1 Mbps	DBPSK	27	11.5	-100
2 Mbps	DQPSK	27	11.5	-96
5.5 Mbps	QPSK	27	11.5	-94
11 Mbps	QPSK	27	11.5	-89
6 Mbps	BPSK	27	11.5	-96
9 Mbps	BPSK	27	11.5	-94
12 Mbps	QPSK	27	11.5	-93
18 Mbps	QPSK	27	11.5	-91
24 Mbps	16-QAM	26	10.5	-86
36 Mbps	16-QAM	26	10.5	-83
48 Mbps	64-QAM	25	10	-80
54 Mbps	64-QAM	24	9.5	-78

TX/RX Specification (11n) – 2412 MHz to 2462 MHz

TX Power per chain (SISO mode), ± 2 dBm.

DC power consumption refers to the total DC power drawn by the module when operating in 2x2 MU-MIMO mode at 2.4 GHz and it includes the ideal mode power consumption.

RX Sensitivity per chain (SISO mode), ± 2 dBm.

Data Rate	Modulation	TX Power (dBm)	DC Power Consumption (Watts)	RX Sensitivity (dBm)
HT20-MCS0	BPSK	27	11.5	-94
HT20-MCS1	QPSK	27	11.5	-90
HT20-MCS2	QPSK	27	11.5	-88
HT20-MCS3	16-QAM	26	10.5	-85
HT20-MCS4	16-QAM	26	10.5	-81
HT20-MCS5	64-QAM	25	10	-77
HT20-MCS6	64-QAM	24	9.75	-76
HT20-MCS7	64-QAM	23	9.5	-74
HT40-MCS0	BPSK	27	11.5	-91
HT40-MCS1	QPSK	27	11.5	-87
HT40-MCS2	QPSK	27	11.5	-85
HT40-MCS3	16-QAM	26	10.5	-82
HT40-MCS4	16-QAM	26	10.5	-78
HT40-MCS5	64-QAM	25	10	-74
HT40-MCS6	64-QAM	24	9.75	-73
HT40-MCS7	64-QAM	23	9.5	-71

TX/RX Specification (11ac) – 2412 MHz to 2462 MHz

TX Power per chain (SISO mode), ± 2 dBm.

DC power consumption refers to the total DC power drawn by the module when operating in 2x2 MU-MIMO mode at 2.4 GHz and it includes the ideal mode power consumption.

RX Sensitivity per chain (SISO mode), ± 2 dBm.

Data Rate	Modulation	TX Power (dBm)	DC Power Consumption (Watts)	RX Sensitivity (dBm)
VHT20-MCS0	BPSK	27	11.5	-96
VHT20-MCS1	QPSK	27	11.5	-94
VHT20-MCS2	QPSK	27	11.5	-92
VHT20-MCS3	16-QAM	26	10.5	-89
VHT20-MCS4	16-QAM	26	10.5	-85
VHT20-MCS5	64-QAM	25	10	-81
VHT20-MCS6	64-QAM	24	9.75	-80
VHT20-MCS7	64-QAM	23	9.5	-79
VHT20-MCS8	256-QAM	22	9.25	-74
VHT20-MCS9	256-QAM	21	9	-72
VHT20-MCS10	1024-QAM	21	9	-69
VHT20-MCS11	1024-QAM	21	9	-67
VHT40-MCS0	BPSK	27	11.5	-93
VHT40-MCS1	QPSK	27	11.5	-91
VHT40-MCS2	QPSK	27	11.5	-89
VHT40-MCS3	16-QAM	26	10.5	-86
VHT40-MCS4	16-QAM	26	10.5	-82
VHT40-MCS5	64-QAM	25	10	-78
VHT40-MCS6	64-QAM	24	9.75	-77
VHT40-MCS7	64-QAM	23	9.5	-76
VHT40-MCS8	256-QAM	22	9.25	-71
VHT40-MCS9	256-QAM	21	9	-69
VHT40-MCS10	1024-QAM	21	9	-66
VHT40-MCS11	1024-QAM	21	9	-64

TX/RX Specification (11ax) – 2412 MHz to 2462 MHz

TX Power per chain (SISO mode), ± 2 dBm.

DC power consumption refers to the total DC power drawn by the module when operating in 2x2 MU-MIMO mode at 2.4 GHz and it includes the ideal mode power consumption.

RX Sensitivity per chain (SISO mode), ± 2 dBm.

Data Rate	Modulation	TX Power (dBm)	DC Power Consumption (Watts)	RX Sensitivity (dBm)
HE20-MCS0	BPSK	27	11.5	-94
HE20-MCS1	QPSK	27	11.5	-93
HE20-MCS2	QPSK	27	11.5	-91
HE20-MCS3	16-QAM	26	10.5	-89
HE20-MCS4	16-QAM	26	10.5	-85
HE20-MCS5	64-QAM	25	10	-81
HE20-MCS6	64-QAM	24	9.75	-80
HE20-MCS7	64-QAM	23	9.5	-78
HE20-MCS8	256-QAM	22	9.25	-75
HE20-MCS9	256-QAM	21	9	-73
HE20-MCS10	1024-QAM	21	9	-70
HE20-MCS11	1024-QAM	21	9	-67
HE40-MCS0	BPSK	27	11.5	-91
HE40-MCS1	QPSK	27	11.5	-90
HE40-MCS2	QPSK	27	11.5	-88
HE40-MCS3	16-QAM	26	10.5	-86
HE40-MCS4	16-QAM	26	10.5	-82
HE40-MCS5	64-QAM	25	10	-78
HE40-MCS6	64-QAM	24	9.75	-77
HE40-MCS7	64-QAM	23	9.5	-75
HE40-MCS8	256-QAM	22	9.25	-72
HE40-MCS9	256-QAM	21	9	-70
HE40-MCS10	1024-QAM	21	9	-67
HE40-MCS11	1024-QAM	21	9	-64

TX Specification - 2412 MHz to 2462 MHz

Parameter	Specification
RF Power control Step	0.5 dBm
Spectral Mask Compliance	Compliant with IEEE 802.11b/g/n/ac/ax Mask, with > 5 dB margin
EVM Compliance	Compliant with IEEE 802.11b/g/n/ac/ax EVM requirement with > 5 dB margin
Second Harmonic Spurious Emission	-30 dBC
Third Harmonic Spurious Emission	-40 dBC
Transmitter Spurious Emission	FCC PART 15C COMPLIANT

RX Specification - 2412 MHz to 2462 MHz

Parameter	Specification
Receiver Maximum input level (10% PER)	
11b, 11g < 18 Mbps, 11n/11ac/11ax < MCS5	> 2 dBm
11b, 11g > 18 Mbps, 11n/11ac/11ax > MCS5	> -10 dBm
Frequency Accuracy	Within \pm 10 PPM
Receiver Adjacent Channel Rejection (ACR)	
11g, 6 Mbps	> 25 dBC
11ac, 11ax, HE40-MCS0	> 30 dBC
11ax, HE40-MCS11	> 11 dBC
Interference De-sensitization 11ax, HE20-MCS13	
400 MHz to 2350 MHz	> 50 dBC
4800 MHz to 5825 MHz	> 60 dBC

TX/RX Specification (11a/n) – 4920 MHz to 5500 MHz

TX Power per chain (SISO mode), ± 2 dBm.

DC power consumption refers to the total DC power drawn by the module when operating in 2x2 MU-MIMO mode at 4.9/5 GHz and it includes the ideal mode power consumption.

RX Sensitivity per chain (SISO mode), ± 2 dBm.

Target Power are defined for 4.9 GHz (4920 MHz-4990 MHz) with channel BW 5/10/20 MHz.

Data Rate	Modulation	TX Power (dBm)	DC Power Consumption (Watts)	RX Sensitivity (dBm)
6 Mbps	BPSK	27	12.5	-94
9 Mbps	BPSK	27	12.5	-92
12 Mbps	QPSK	26	11.5	-91
18 Mbps	QPSK	26	11.5	-90
24 Mbps	16-QAM	25	10.5	-85
36 Mbps	16-QAM	24	10	-82
48 Mbps	64-QAM	23	9.5	-77
54 Mbps	64-QAM	22	9	-76
HT20-MCS0	BPSK	27	12.5	-92
HT20-MCS1	QPSK	26	11.5	-89
HT20-MCS2	QPSK	26	11.5	-87
HT20-MCS3	16-QAM	24	10	-83
HT20-MCS4	16-QAM	24	10	-80
HT20-MCS5	64-QAM	23	9.5	-76
HT20-MCS6	64-QAM	21	8.5	-74
HT20-MCS7	64-QAM	21	8.5	-73
HT40-MCS0	BPSK	27	12.5	-89
HT40-MCS1	QPSK	26	11.5	-86
HT40-MCS2	QPSK	26	11.5	-84
HT40-MCS3	16-QAM	24	10	-80
HT40-MCS4	16-QAM	22	9	-77
HT40-MCS5	64-QAM	22	9	-73
HT40-MCS6	64-QAM	21	8.5	-71
HT40-MCS7	64-QAM	21	8.5	-70

TX/RX Specification (11a/n) – 5500 MHz to 5700 MHz

TX Power per chain (SISO mode), ± 2 dBm.

DC power consumption refers to the total DC power drawn by the module when operating in 2x2 MU-MIMO mode at 5 GHz and it includes the ideal mode power consumption.

RX Sensitivity per chain (SISO mode), ± 2 dBm.

Data Rate	Modulation	TX Power per chain (dBm)	DC Power Consumption (Watts)	RX Sensitivity (dBm)
6 Mbps	BPSK	27	12.5	-94
9 Mbps	BPSK	27	12.5	-92
12 Mbps	QPSK	27	12.5	-91
18 Mbps	QPSK	27	12.5	-90
24 Mbps	16-QAM	25	10.5	-85
36 Mbps	16-QAM	25	10.5	-82
48 Mbps	64-QAM	24	10	-77
54 Mbps	64-QAM	23	9.5	-76
HT20-MCS0	BPSK	27	12.5	-92
HT20-MCS1	QPSK	27	12.5	-89
HT20-MCS2	QPSK	27	12.5	-87
HT20-MCS3	16-QAM	25	10.5	-83
HT20-MCS4	16-QAM	25	10.5	-80
HT20-MCS5	64-QAM	24	10	-76
HT20-MCS6	64-QAM	23	9.5	-74
HT20-MCS7	64-QAM	22	9	-73
HT40-MCS0	BPSK	27	12.5	-89
HT40-MCS1	QPSK	26	11.5	-86
HT40-MCS2	QPSK	26	11.5	-84
HT40-MCS3	16-QAM	25	10.5	-80
HT40-MCS4	16-QAM	22	9	-77
HT40-MCS5	64-QAM	22	9	-73
HT40-MCS6	64-QAM	21	8.5	-71
HT40-MCS7	64-QAM	21	8.5	-70

TX/RX Specification (11a/n) – 5700 MHz to 5860 MHz

TX Power per chain (SISO mode), ± 2 dBm.

DC power consumption refers to the total DC power drawn by the module when operating in 2x2 MU-MIMO mode at 5 GHz and it includes the ideal mode power consumption.

RX Sensitivity per chain (SISO mode), ± 2 dBm.

Data Rate	Modulation	TX Power per chain (dBm)	DC Power Consumption (Watts)	RX Sensitivity (dBm)
6 Mbps	BPSK	27	12.5	-94
9 Mbps	BPSK	27	12.5	-92
12 Mbps	QPSK	26	11.5	-91
18 Mbps	QPSK	26	11.5	-90
24 Mbps	16-QAM	25	10.5	-85
36 Mbps	16-QAM	24	10	-82
48 Mbps	64-QAM	23	9.5	-77
54 Mbps	64-QAM	22	9	-76
HT20-MCS0	BPSK	27	12.5	-92
HT20-MCS1	QPSK	26	11.5	-89
HT20-MCS2	QPSK	26	11.5	-87
HT20-MCS3	16-QAM	24	10	-83
HT20-MCS4	16-QAM	23	9.5	-80
HT20-MCS5	64-QAM	23	9.5	-76
HT20-MCS6	64-QAM	22	9	-74
HT20-MCS7	64-QAM	21	8.5	-73
HT40-MCS0	BPSK	27	12.5	-89
HT40-MCS1	QPSK	26	11.5	-86
HT40-MCS2	QPSK	26	11.5	-84
HT40-MCS3	16-QAM	25	10.5	-80
HT40-MCS4	16-QAM	22	9	-77
HT40-MCS5	64-QAM	22	9	-73
HT40-MCS6	64-QAM	21	8.5	-71
HT40-MCS7	64-QAM	21	8.5	-70

TX/RX Specification (11ac) – 4920 MHz to 5500 MHz

TX Power per chain (SISO mode), ± 2 dBm.

DC power consumption refers to the total DC power drawn by the module when operating in 2x2 MU-MIMO mode at 4.9/5 GHz and it includes the ideal mode power consumption.

RX Sensitivity per chain (SISO mode), ± 2 dBm.

Target Power are defined for 4.9 GHz (4920 MHz-4990 MHz) with channel BW 5/10/20 MHz.

Data Rate	Modulation	TX Power (dBm)	DC Power Consumption (Watts)	RX Sensitivity (dBm)
VHT20-MCS0	BPSK	27	12.5	-95
VHT20-MCS1	QPSK	26	11.5	-93
VHT20-MCS2	QPSK	26	11.5	-91
VHT20-MCS3	16-QAM	24	10	-88
VHT20-MCS4	16-QAM	24	10	-84
VHT20-MCS5	64-QAM	23	9	-80
VHT20-MCS6	64-QAM	22	8.5	-79
VHT20-MCS7	64-QAM	21	8.5	-78
VHT20-MCS8	256-QAM	20	8.5	-73
VHT20-MCS9	256-QAM	20	8.5	-71
VHT20-MCS10	1024-QAM	19	8.5	-68
VHT20-MCS11	1024-QAM	19	8.5	-66
VHT40-MCS0	BPSK	27	12.5	-92
VHT40-MCS1	QPSK	26	11.5	-90
VHT40-MCS2	QPSK	26	11.5	-88
VHT40-MCS3	16-QAM	24	10	-85
VHT40-MCS4	16-QAM	22	9	-81
VHT40-MCS5	64-QAM	22	9	-77
VHT40-MCS6	64-QAM	21	8.5	-76
VHT40-MCS7	64-QAM	21	8.5	-75
VHT40-MCS8	256-QAM	20	8.5	-70
VHT40-MCS9	256-QAM	20	8.5	-68
VHT40-MCS10	1024-QAM	18	8.5	-65
VHT40-MCS11	1024-QAM	18	8.5	-63

TX/RX Specification (11ac) – 4920 MHz to 5500 MHz

TX Power per chain (SISO mode), ± 2 dBm.

DC power consumption refers to the total DC power drawn by the module when operating in 2x2 MU-MIMO mode at 4.9/5 GHz and it includes the ideal mode power consumption.

RX Sensitivity per chain (SISO mode), ± 2 dBm.

Target Power are defined for 4.9 GHz (4920 MHz-4990 MHz) with channel BW 5/10/20 MHz.

Data Rate	Modulation	TX Power (dBm)	DC Power Consumption (Watts)	RX Sensitivity (dBm)
VHT80-MCS0	BPSK	27	12.5	-89
VHT80-MCS1	QPSK	26	11.5	-87
VHT80-MCS2	QPSK	26	11.5	-85
VHT80-MCS3	16-QAM	24	10	-82
VHT80-MCS4	16-QAM	22	9	-78
VHT80-MCS5	64-QAM	22	9	-74
VHT80-MCS6	64-QAM	21	8.5	-73
VHT80-MCS7	64-QAM	21	8.5	-72
VHT80-MCS8	256-QAM	20	8.5	-67
VHT80-MCS9	256-QAM	20	8.5	-65
VHT80-MCS10	1024-QAM	18	8.5	-62
VHT80-MCS11	1024-QAM	18	8.5	-60

TX/RX Specification (11ac) – 5500 MHz to 5700 MHz

TX Power per chain (SISO mode), ± 2 dBm.

DC power consumption refers to the total DC power drawn by the module when operating in 2x2 MU-MIMO mode at 5 GHz and it includes the ideal mode power consumption.

RX Sensitivity per chain (SISO mode), ± 2 dBm.

Data Rate	Modulation	TX Power (dBm)	DC Power Consumption (Watts)	RX Sensitivity (dBm)
VHT20-MCS0	BPSK	27	12.5	-95
VHT20-MCS1	QPSK	27	12.5	-93
VHT20-MCS2	QPSK	27	12.5	-91
VHT20-MCS3	16-QAM	25	10.5	-88
VHT20-MCS4	16-QAM	25	10.5	-84
VHT20-MCS5	64-QAM	24	10	-80
VHT20-MCS6	64-QAM	23	9.5	-79
VHT20-MCS7	64-QAM	22	9	-78
VHT20-MCS8	256-QAM	22	9	-73
VHT20-MCS9	256-QAM	21	8.5	-71
VHT20-MCS10	1024-QAM	21	8.5	-68
VHT20-MCS11	1024-QAM	21	8.5	-66
VHT40-MCS0	BPSK	27	12.5	-92
VHT40-MCS1	QPSK	26	11.5	-90
VHT40-MCS2	QPSK	26	11.5	-88
VHT40-MCS3	16-QAM	25	10.5	-85
VHT40-MCS4	16-QAM	23	9.5	-81
VHT40-MCS5	64-QAM	23	9.5	-77
VHT40-MCS6	64-QAM	22	9	-76
VHT40-MCS7	64-QAM	21	8.5	-75
VHT40-MCS8	256-QAM	21	8.5	-70
VHT40-MCS9	256-QAM	21	8.5	-68
VHT40-MCS10	1024-QAM	20	8.5	-65
VHT40-MCS11	1024-QAM	20	8.5	-63

TX/RX Specification (11ac) – 5500 MHz to 5700 MHz

TX Power per chain (SISO mode), ± 2 dBm.

DC power consumption refers to the total DC power drawn by the module when operating in 2x2 MU-MIMO mode at 5 GHz and it includes the ideal mode power consumption.

RX Sensitivity per chain (SISO mode), ± 2 dBm.

Data Rate	Modulation	TX Power (dBm)	DC Power Consumption (Watts)	RX Sensitivity (dBm)
VHT80-MCS0	BPSK	27	12.5	-89
VHT80-MCS1	QPSK	27	12.5	-87
VHT80-MCS2	QPSK	25	10.5	-85
VHT80-MCS3	16-QAM	24	10	-82
VHT80-MCS4	16-QAM	23	9.5	-78
VHT80-MCS5	64-QAM	23	9.5	-74
VHT80-MCS6	64-QAM	22	9	-73
VHT80-MCS7	64-QAM	22	9	-72
VHT80-MCS8	256-QAM	21	8.5	-67
VHT80-MCS9	256-QAM	20	8.5	-65
VHT80-MCS10	1024-QAM	19	8.5	-62
VHT80-MCS11	1024-QAM	19	8.5	-60

TX/RX Specification (11ac) – 5700 MHz to 5860 MHz

TX Power per chain (SISO mode), ± 2 dBm.

DC power consumption refers to the total DC power drawn by the module when operating in 2x2 MU-MIMO mode at 5 GHz and it includes the ideal mode power consumption.

RX Sensitivity per chain (SISO mode), ± 2 dBm.

Data Rate	Modulation	TX Power (dBm)	DC Power Consumption (Watts)	RX Sensitivity (dBm)
VHT20-MCS0	BPSK	27	12.5	-95
VHT20-MCS1	QPSK	26	11.5	-93
VHT20-MCS2	QPSK	26	11.5	-91
VHT20-MCS3	16-QAM	24	10	-88
VHT20-MCS4	16-QAM	23	9.5	-84
VHT20-MCS5	64-QAM	23	9.5	-80
VHT20-MCS6	64-QAM	21	8.5	-79
VHT20-MCS7	64-QAM	21	8.5	-78
VHT20-MCS8	256-QAM	21	8.5	-73
VHT20-MCS9	256-QAM	20	8.5	-71
VHT20-MCS10	1024-QAM	18	8.5	-68
VHT20-MCS11	1024-QAM	17	8.5	-66
VHT40-MCS0	BPSK	27	12.5	-92
VHT40-MCS1	QPSK	26	11.5	-90
VHT40-MCS2	QPSK	26	11.5	-88
VHT40-MCS3	16-QAM	25	10.5	-85
VHT40-MCS4	16-QAM	22	9	-81
VHT40-MCS5	64-QAM	22	9	-77
VHT40-MCS6	64-QAM	21	8.5	-76
VHT40-MCS7	64-QAM	21	8.5	-75
VHT40-MCS8	256-QAM	20	8.5	-70
VHT40-MCS9	256-QAM	20	8.5	-68
VHT40-MCS10	1024-QAM	17	8.5	-65
VHT40-MCS11	1024-QAM	17	8.5	-63

TX/RX Specification (11ac) – 5700 MHz to 5860 MHz

TX Power per chain (SISO mode), ± 2 dBm.

DC power consumption refers to the total DC power drawn by the module when operating in 2x2 MU-MIMO mode at 5 GHz and it includes the ideal mode power consumption.

RX Sensitivity per chain (SISO mode), ± 2 dBm.

Data Rate	Modulation	TX Power (dBm)	DC Power Consumption (Watts)	RX Sensitivity (dBm)
VHT80-MCS0	BPSK	27	12.5	-89
VHT80-MCS1	QPSK	27	12.5	-87
VHT80-MCS2	QPSK	26	11.5	-85
VHT80-MCS3	16-QAM	25	10.5	-82
VHT80-MCS4	16-QAM	24	10	-78
VHT80-MCS5	64-QAM	23	9.5	-74
VHT80-MCS6	64-QAM	22	9	-73
VHT80-MCS7	64-QAM	22	9	-72
VHT80-MCS8	256-QAM	21	8.5	-67
VHT80-MCS9	256-QAM	20	8.5	-65
VHT80-MCS10	1024-QAM	19	8.5	-62
VHT80-MCS11	1024-QAM	19	8.5	-60

TX/RX Specification (11ax) – 4920 MHz to 5500 MHz

TX Power per chain (SISO mode), ± 2 dBm.

DC power consumption refers to the total DC power drawn by the module when operating in 2x2 MU-MIMO mode at 4.9/5 GHz and it includes the ideal mode power consumption.

RX Sensitivity per chain (SISO mode), ± 2 dBm.

Target Power are defined for 4.9 GHz (4920 MHz-4990 MHz) with channel BW 5/10/20 MHz.

Data Rate	Modulation	TX Power (dBm)	DC Power Consumption (Watts)	RX Sensitivity (dBm)
HE20-MCS0	BPSK	27	12.5	-93
HE20-MCS1	QPSK	27	12.5	-92
HE20-MCS2	QPSK	26	11.5	-90
HE20-MCS3	16-QAM	24	10	-88
HE20-MCS4	16-QAM	24	10	-84
HE20-MCS5	64-QAM	23	9.5	-80
HE20-MCS6	64-QAM	22	9	-78
HE20-MCS7	64-QAM	21	8.5	-76
HE20-MCS8	256-QAM	20	8.5	-73
HE20-MCS9	256-QAM	20	8.5	-71
HE20-MCS10	1024-QAM	18	8.5	-68
HE20-MCS11	1024-QAM	18	8.5	-65
HE40-MCS0	BPSK	27	12.5	-90
HE40-MCS1	QPSK	26	11.5	-89
HE40-MCS2	QPSK	26	11.5	-87
HE40-MCS3	16-QAM	24	10	-85
HE40-MCS4	16-QAM	24	10	-81
HE40-MCS5	64-QAM	23	9.5	-77
HE40-MCS6	64-QAM	22	9	-75
HE40-MCS7	64-QAM	21	8.5	-73
HE40-MCS8	256-QAM	20	8.5	-70
HE40-MCS9	256-QAM	19	8.5	-68
HE40-MCS10	1024-QAM	18	8.5	-65
HE40-MCS11	1024-QAM	18	8.5	-62

TX/RX Specification (11ax) – 4920 MHz to 5500 MHz

TX Power per chain (SISO mode), ± 2 dBm.

DC power consumption refers to the total DC power drawn by the module when operating in 2x2 MU-MIMO mode at 4.9/5 GHz and it includes the ideal mode power consumption.

RX Sensitivity per chain (SISO mode), ± 2 dBm.

Target Power are defined for 4.9 GHz (4920 MHz-4990 MHz) with channel BW 5/10/20 MHz.

Data Rate	Modulation	TX Power (dBm)	DC Power Consumption (Watts)	RX Sensitivity (dBm)
HE80-MCS0	BPSK	27	12.5	-87
HE80-MCS1	QPSK	26	11.5	-86
HE80-MCS2	QPSK	26	11.5	-84
HE80-MCS3	16-QAM	24	10	-82
HE80-MCS4	16-QAM	24	10	-78
HE80-MCS5	64-QAM	23	9.5	-74
HE80-MCS6	64-QAM	22	9	-72
HE80-MCS7	64-QAM	21	8.5	-70
HE80-MCS8	256-QAM	20	8.5	-67
HE80-MCS9	256-QAM	19	8.5	-65
HE80-MCS10	1024-QAM	18	8.5	-62
HE80-MCS11	1024-QAM	18	8.5	-59

TX/RX Specification (11ax) – 5500 MHz to 5700 MHz

TX Power per chain (SISO mode), ± 2 dBm.

DC power consumption refers to the total DC power drawn by the module when operating in 2x2 MU-MIMO mode at 5 GHz and it includes the ideal mode power consumption.

RX Sensitivity per chain (SISO mode), ± 2 dBm.

Data Rate	Modulation	TX Power (dBm)	DC Power Consumption (Watts)	RX Sensitivity (dBm)
HE20-MCS0	BPSK	27	12.5	-93
HE20-MCS1	QPSK	27	12.5	-92
HE20-MCS2	QPSK	27	12.5	-90
HE20-MCS3	16-QAM	25	10.5	-88
HE20-MCS4	16-QAM	25	10.5	-84
HE20-MCS5	64-QAM	23	9.5	-80
HE20-MCS6	64-QAM	22	9	-78
HE20-MCS7	64-QAM	22	9	-76
HE20-MCS8	256-QAM	21	8.5	-73
HE20-MCS9	256-QAM	21	8.5	-71
HE20-MCS10	1024-QAM	20	8.5	-68
HE20-MCS11	1024-QAM	20	8.5	-65
HE40-MCS0	BPSK	27	12.5	-90
HE40-MCS1	QPSK	26	11.5	-89
HE40-MCS2	QPSK	26	11.5	-87
HE40-MCS3	16-QAM	25	10.5	-85
HE40-MCS4	16-QAM	24	10	-81
HE40-MCS5	64-QAM	23	9.5	-77
HE40-MCS6	64-QAM	22	9	-75
HE40-MCS7	64-QAM	21	8.5	-73
HE40-MCS8	256-QAM	21	8.5	-70
HE40-MCS9	256-QAM	21	8.5	-68
HE40-MCS10	1024-QAM	20	8.5	-65
HE40-MCS11	1024-QAM	20	8.5	-62

TX/RX Specification (11ax) – 5500 MHz to 5700 MHz

TX Power per chain (SISO mode), ± 2 dBm.

DC power consumption refers to the total DC power drawn by the module when operating in 2x2 MU-MIMO mode at 5 GHz and it includes the ideal mode power consumption.

RX Sensitivity per chain (SISO mode), ± 2 dBm.

Data Rate	Modulation	TX Power (dBm)	DC Power Consumption (Watts)	RX Sensitivity (dBm)
HE80-MCS0	BPSK	27	12.5	-87
HE80-MCS1	QPSK	27	12.5	-86
HE80-MCS2	QPSK	26	11.5	-84
HE80-MCS3	16-QAM	24	10	-82
HE80-MCS4	16-QAM	24	10	-78
HE80-MCS5	64-QAM	23	9.5	-74
HE80-MCS6	64-QAM	22	9	-72
HE80-MCS7	64-QAM	22	9	-70
HE80-MCS8	256-QAM	21	8.5	-67
HE80-MCS9	256-QAM	20	8.5	-65
HE80-MCS10	1024-QAM	19	8.5	-62
HE80-MCS11	1024-QAM	19	8.5	-59

TX/RX Specification (11ax) – 5700 MHz to 5860 MHz

TX Power per chain (SISO mode), ± 2 dBm.

DC power consumption refers to the total DC power drawn by the module when operating in 2x2 MU-MIMO mode at 5 GHz and it includes the ideal mode power consumption.

RX Sensitivity per chain (SISO mode), ± 2 dBm.

Data Rate	Modulation	TX Power (dBm)	DC Power Consumption (Watts)	RX Sensitivity (dBm)
HE20-MCS0	BPSK	27	12.5	-93
HE20-MCS1	QPSK	27	12.5	-92
HE20-MCS2	QPSK	26	11.5	-90
HE20-MCS3	16-QAM	24	10	-88
HE20-MCS4	16-QAM	24	10	-84
HE20-MCS5	64-QAM	23	9.5	-80
HE20-MCS6	64-QAM	22	9	-78
HE20-MCS7	64-QAM	21	8.5	-76
HE20-MCS8	256-QAM	20	8.5	-73
HE20-MCS9	256-QAM	20	8.5	-71
HE20-MCS10	1024-QAM	17	8.5	-68
HE20-MCS11	1024-QAM	17	8.5	-65
HE40-MCS0	BPSK	27	12.5	-90
HE40-MCS1	QPSK	26	11.5	-89
HE40-MCS2	QPSK	26	11.5	-87
HE40-MCS3	16-QAM	25	10.5	-85
HE40-MCS4	16-QAM	24	10	-81
HE40-MCS5	64-QAM	23	9.5	-77
HE40-MCS6	64-QAM	22	9	-75
HE40-MCS7	64-QAM	21	8.5	-73
HE40-MCS8	256-QAM	20	8.5	-70
HE40-MCS9	256-QAM	19	8.5	-68
HE40-MCS10	1024-QAM	17	8.5	-65
HE40-MCS11	1024-QAM	17	8.5	-62

TX/RX Specification (11ax) – 5700 MHz to 5860 MHz

TX Power per chain (SISO mode), ± 2 dBm.

DC power consumption refers to the total DC power drawn by the module when operating in 2x2 MU-MIMO mode at 5 GHz and it includes the ideal mode power consumption.

RX Sensitivity per chain (SISO mode), ± 2 dBm.

Data Rate	Modulation	TX Power (dBm)	DC Power Consumption (Watts)	RX Sensitivity (dBm)
HE80-MCS0	BPSK	27	12.5	-87
HE80-MCS1	QPSK	27	12.5	-86
HE80-MCS2	QPSK	26	11.5	-84
HE80-MCS3	16-QAM	25	10.5	-82
HE80-MCS4	16-QAM	24	10	-78
HE80-MCS5	64-QAM	23	9.5	-74
HE80-MCS6	64-QAM	22	9	-72
HE80-MCS7	64-QAM	22	9	-70
HE80-MCS8	256-QAM	21	8.5	-67
HE80-MCS9	256-QAM	20	8.5	-65
HE80-MCS10	1024-QAM	18	8.5	-62
HE80-MCS11	1024-QAM	18	8.5	-59

TX Specification - 4900 MHz to 5900 MHz

Parameter	Specification
RF Power control Step	0.5 dBm
Spectral Mask Compliance	Compliant with IEEE 802.11an/ac/ax Mask, with > 5 dB margin
EVM Compliance	Compliant with IEEE 802.11a/n/ac/ax EVM requirement with > 5 dB margin
Second Harmonic Spurious Emission	-60 dBC
Third Harmonic Spurious Emission	-70 dBC
Transmitter Spurious Emission	FCC PART 15E COMPLIANT

RX Specification - 4900 MHz to 5900 MHz


Parameter	Specification
Receiver Maximum input level (10% PER)	
11a < 18 Mbps, 11n/11ac/11ax < MCS5	> 2 dBm
11a > 18 Mbps, 11n/11ac/11ax > MCS5	> -10 dBm
Frequency Accuracy	Within ± 10 PPM
Receiver Adjacent Channel Rejection (ACR)	
11n, 6 Mbps	> 25 dBC
11ac VHT40, 11ax HE80-MCS0	> 30 dBC
11ax, HE160-MCS11	> 11 dBC
Interference De-sensitization 11ax, HE20-MCS13	
400 MHz to 2350 MHz	> 70 dBC
2400 MHz to 3600 MHz	> 40 dBC
In Band Interference	> 30 dBC

CONNECTION DETAILS








REF	PART
1,2	SMA Connector, 4.9/5 GHz (Ant1,Ant2)
3,4	SMA Connector, 2.4 GHz (Ant1,Ant2)
5	Power Connector, JST SM04B-GHS-TB
6	Ethernet Connector, HIROSE IX60G-A-10P
7	USB Type-A Connector for USB 2.0
8	RGB LED
9	USB Micro-B Connector for UART
10	JST SM08B-GHS-TB for EJTAG (On bottom side)
11	USB, Type-C Connector for USB 3.0
12	SD Card Connector

CONNECTION PIN-OUT



CONNECTOR	PIN#	PIN DESCRIPTION
ANTENNA	1	5 GHz Ant1
	2	5 GHz Ant2
	3	2.4 GHz Ant1
	4	2.4 GHZ Ant2
POWER	JST SM04B-GHS-TB – Pin-1 (from left-to-down on Top side)	
	JST SM04B-GHS-TB – Pin-2 (from left-to-down on Top side)	
	JST SM04B-GHS-TB – Pin-3 (from left-to-down on Top side)	
	JST SM04B-GHS-TB – Pin-4 (from left-to-down on Top side)	
E-JTAG	JST SM08B-GHS-TB – Pin-1 (from left-to-right on Top side)	
	JST SM08B-GHS-TB – Pin-2 (from left-to-right on Top side)	
	JST SM08B-GHS-TB – Pin-3 (from left-to-right on Top side)	
	JST SM08B-GHS-TB – Pin-4 (from left-to-right on Top side)	
	JST SM08B-GHS-TB – Pin-5 (from left-to-right on Top side)	
	JST SM08B-GHS-TB – Pin-6 (from left-to-right on Top side)	
	JST SM08B-GHS-TB – Pin-7 (from left-to-right on Top side)	
	JST SM08B-GHS-TB – Pin-8 (from left-to-right on Top side)	

MECHANICAL DIMENSIONS



Trademarks

The information in this document is being provided in connection with Vizmonet products, which are subject to continuous developments and improvements. While every effort is made to ensure that the information contained in this document is correct and accurate at the time of this printing, Vizmonet makes no representations or warranties with respect to the accuracy of the information and is not liable for errors or mistakes that may arise. However, Vizmonet reserves the right to make changes to specifications and product descriptions at any time without notice. Vizmonet does not assume any responsibility for the use of the described product; neither does it convey any license under its patent rights, or the rights of others. Vizmonet products are not intended, authorized, or warranted for use as components in applications intended to support or sustain life. Built-to-Customize™ is a trademark of Vizmonet. All other trademarks, registered trademarks and product names are the sole property of their respective owners.

Contact

Web: <https://vizmonet.com>
Email: enquiry@vizmonet.com

Headquarters

Vizmonet Pte Ltd
21, Woodlands Close
#03-01, Primz Biz Hub
Singapore 737 854